

特定小電カトランシーパー（特小）チャンネル互換表

	周波数 (MHz)		icom	モトローラ		八重洲無線		JVCケン ウッド	wave CSR
				通常	CL40・CL40L CL45・ CL70A CL120A	スタンダード (FTHシリー ズ) (PKシ リーズ)	スタンダード (HXシリー ズ)		
単信 11ch	422.0500		1	1	1	1	1	1	1
	422.0625		2	2	2	2	2	2	2
	422.0750		3	3	3	3	3	3	3
	422.0875		4	4	4	4	4	4	4
	422.1000		5	5	5	5	5	5	5
	422.1125		6	6	6	6	6	6	6
	422.1250		7	7	7	7	7	7	7
	422.1375		8	8	8	8	8	8	8
	422.1500		9	9	9	9	9	9	9
	422.1625		10	10	10	10	10	10	10
	422.1750		11	11	11	11	11	11	11
単信 9ch	422.2000		12	12	1	1	1	h1	12
	422.2125		13	13	2	2	2	h2	13
	422.2250		14	14	3	3	3	h3	14
	422.2375		15	15	4	4	4	h4	15
	422.2500		16	16	5	5	5	h5	16
	422.2625		17	17	6	6	6	h6	17
	422.2750		18	18	7	7	7	h7	18
	422.2875		19	19	8	8	8	h8	19
422.3000		20	20	9	9	9	h9	20	
中継 18ch	440.0250	421.5750	1	21	12	12	中継01	1	1
	440.0375	421.5875	2	22	13	13	中継02	2	2
	440.0500	421.6000	3	23	14	14	中継03	3	3
	440.0625	421.6125	4	24	15	15	中継04	4	4
	440.0750	421.6250	5	25	16	16	中継05	5	5
	440.0875	421.6375	6	26	17	17	中継06	6	6
	440.1000	421.6500	7	27	18	18	中継07	7	7
	440.1125	421.6625	8	28	19	19	中継08	8	8
	440.1250	421.6750	9	29	20	20	中継09	9	9
	440.1375	421.6875	10	30	21	21	中継10	10	10
	440.1500	421.7000	11	31	22	22	中継11	11	11
	440.1625	421.7125	12	32	23	23	中継12	12	12
	440.1750	421.7250	13	33	24	24	中継13	13	13
	440.1875	421.7375	14	34	25	25	中継14	14	14
	440.2000	421.7500	15	35	26	26	中継15	15	15
	440.2125	421.7625	16	36	27	27	中継16	16	16
	440.2250	421.7750	17	37	28	28	中継17	17	17
	440.2375	421.7875	18	38	29	29	中継18	18	18
中継 9ch	440.2625	421.8125	19	39	1-0	1-0	中継1	CHh1	19
	440.2750	421.8250	20	40	1-1	1-1	中継2	CHh2	20
	440.2875	421.8375	21	41	1-2	1-2	中継3	CHh3	21
	440.3000	421.8500	22	42	1-3	1-3	中継4	CHh4	22
	440.3125	421.8625	23	43	1-4	1-4	中継5	CHh5	23
	440.3250	421.8750	24	44	1-5	1-5	中継6	CHh6	24
	440.3250	421.8875	25	45	1-6	1-6	中継7	CHh7	25
	440.3250	421.9000	26	46	1-7	1-7	中継8	CHh8	26
440.3625	421.9125	27	47	1-8	1-8	中継9	CHh9	27	